

PA 4*5 Matrix Mixer Amplifier +USB/SD/FM/BLUETOOTH, 60W & 120W

SP-MX460 & SP-MX4120

Feature:

- 4x4 Audio Matrix mixer amplifier with 4*120W or 4*60W output.
- Designed for multi-room systems requiring different audio sources.
- 4 independent output zones for multiple room sound system.
- 5 Channel independent output.
- 6 sources matrix distributed to any of the 4 speaker zones.
- 5 Signal input: Mic 1-3 switchable phantom power, 2 RCA and One with priority function.
- Different 4 zone of different music program and different volume output.
- 4 Zone speaker outputs of 100V or 70V, 4-16 Ohms speakers.
- 100V/70V or 4-16 Ohms operation for PA system and hi-fi both sound system.
- Mp3 audio input, support USB/SD/FM/Bluetooth can be matrix switched to any of the 4 zones independently.
- Internal Bluetooth receiver with mobile use
- Telephone audio input with priority function.
- Monitor function.



Specification:

Model	SP-MX460	SP-MX4120
Description	4x5 Matrix Mixer Amplifier with with Mp3 USB/SD/FM/Bluetooth	
Rated Power	4*60W	4*120W
Speaker Output	100V or 70V, 4-16 Ohms	
Input	Mic/Line1-3 with switchable phantom power AUX1-2 500mV/10K ohm/MIC1-3 1-6mV/ MIC1 at 48V	
Frequency Response	80Hz~20KHz	
Distortion(THD)	<0.5% at 1KHz 100V -3dB	
S/N Ratio	75dB	
Tone Control	Bass: 100Hz +-10dB, Treble: 10KHz +-10dB	
Power Supply	AC 110V-240V 50-60Hz	
Dimension	485(W)×340(D)×88(H)mm	
Weight	15KG	22KG

